

GENREADY LOAD CENTER AND TRANSFER SWITCH



DESCRIPTION

The GenReady load center is a hybrid panel that operates as a normal load center and also allows for seamless integration of standby generators.


GENREADY™ LOAD CENTER FEATURES

- 40 circuit capacity with the use of tandem breakers
- Dimensions are the same as a standard 42-space main load center
- Utilizes standard Siemens components
- Protect up to 18 circuits, up to 30 with the use of tandem breakers
- 10 circuits available for non-protected loads
- Circuits can easily be shifted from protected to non-protected and vice versa
- UL listed and service entrance rated
- Models available with or without EZ Transfer operator factory installed
- Single panels are compatible with generators rated up to 125 Amps/30 kW
- Multiple GenReady load centers can be supported with a single generator
- Flush Mount NEMA 1 Enclosure



EZ TRANSFER™ OPERATOR FEATURES

- Factory installed on the GenReady Advanced model. Can be easily installed in the field on the GenReady Basic with available kit
- Allows for manual or automatic operation



Please Note: The GenReady Panel is designed to be directly compatible with any Generac manufactured product. Use of another manufacturer's generator may require the purchase and installation of additional sensing and control components.

GENERAC®
POWER SYSTEMS, INC.

PRODUCT OPTIONS

GenReady Load Center and Transfer Switch

GenReady Basic Load Center
Model Number 5448



Includes:

- 125A Circuit Breaker
- 125A Lower Panel Circuit Switch
- 200A Main Circuit Breaker


GenReady Advanced Load Center
with EZ Transfer™ Operator
Model Number 5449



Includes GenReady Basic plus:

- EZ Transfer™ Operator
- 125A Lower Panel, Generator Circuit Switch
- 15A Double Pole Breaker for Sensing Circuit
- Plus all other components found in the field installation kit.

EZ Transfer Operator
Field Installation Kit
Model Number 5447




Transfer Operator Field Installation Kit Includes:

- Transfer Operator
- 15A Double Pole Breaker for Generator Sensing Circuit
- 125A Lower Panel, Generator Circuit Switch
- Hold Down Bracket
- Interlock Bar
- Mounting Hardware
- Decals
- Installation Guide


INSTALLATION OPTIONS

GenReady Basic




The GenReady load center is installed without the EZ Transfer operator. It replaces the home's main load center. This option will save the homeowner thousands in upgrade costs when a generator is installed.

GenReady Advanced




The GenReady load center is installed with the EZ Transfer operator. All fuel and electrical lines (contractor supplied) are installed to the planned generator site along with the generator pad (if required). The home is completely wired and ready for the addition of a generator in the future.


GenReady Complete



Everything included in the GenReady Advanced level is installed along with an automatic standby generator. The home's selected circuits will be backed up by generator power whenever the utility is lost.

INTERCONNECTIONS





ALL WIRING TO BE MINIMUM 18AWG, 300VAC RATING.
RECOMMENDED WIRE TYPE: THHN



NOTE: INSTALLATION TO BE DONE BY A
LICENSED ELECTRICIAN AND MUST
MEET ALL NATIONAL, STATE AND
LOCAL ELECTRICAL CODES.

GEN-READY
LOAD CENTER

PRODUCT USAGE: 2008 & LATER, HSB.

UNIT DIMENSIONS

GenReady Load Center and Transfer Switch



SPECIFICATIONS

GenReady Load Center and Transfer Switch

Enclosure.....	NEMA Type 1, general purpose, painted metal
Main Breaker	200 Amp
Generator Switch	125 Amp
Main breaker wire size	# 1 to 300 mcm Cu-Al
Generator switch wire size	# 2 to 1/0 Cu, 1/0-2/0 Al
Neutral Lug	# 6 to 300 mcm
Ground Lug	# 14- 2/0
Ground Fault or Arc Fault Circuit Breaker	QPF or QAF Siemens
Maximum number of circuits (standard 1" breakers / tandem 1/2" breakers)	
Protected circuits.....	18/30
Non-protected circuits	10/NA
Total circuits	28/40
Withstand rating Main bus (amps)	22,000
Meets NEC wire bending space.....	Yes
UL listed	Yes
Seismically qualified to meet UBC code	Yes
Weight – GenReady Basic w/o EZ transfer operator (GenReady Advanced with EZ transfer operator)	45.5 lbs. (49 lbs.)
Operating temperature range	-20° F to 140° F

GENERAC[®]
POWER SYSTEMS, INC.

GENERAC POWER SYSTEMS, INC. • P.O. BOX 8 • WAUKESHA, WI 53187
262/544-4811 • FAX 262/544-4851
